

Math 399 Lab III - Spring 2018

Real Head HRTF Measurements

Please submit all lab report parts on the Moodle page for MAT399.

Time-stamp determines the submit time, due by midnight on the due-date.

Due: Monday, March 12

In the lab, follow the calibration and settings outlined by Professor Dixon, and use the same chirp signals as you did in the previous two labs.

For this lab, you will do the same measurements that you did for the dummy head but in this case you will use your own head.

Use these settings to set up the recording system, and record chirp responses to the following chirp signals, with sample rate 44.1 kHz, each going from 20 Hz to 20 kHz:

1. duration 256 samples
2. duration 512 samples
3. duration 1024 samples
4. duration 2048 samples
5. duration 100 milliseconds
6. duration 500 milliseconds
7. duration 1000 milliseconds
8. duration 2000 milliseconds

Try to position your head on the same plane as the midpoint between the top and bottom drivers on the speaker. Record the chirp signals once for each azimuth angle going from -90 to 90 degrees (coordinate system A in the text) using increments of 30 degrees.

For this lab, write up a report and submit to Moodle with your wave files all in one folder. The report should describe any particular apparatus that you used to set up the measurements.